

FX LUMINAIRE STAINLESS STEEL
POTENZA X TRANSFORMER.
SEE LIGHTING PLAN FOR WATTAGE, SIZE
AND SWITCHING TYPE.

MOUNT BEHIND PLANT MATERIAL OR
BOULDERS TO OBSCURE A DIRECT VIEW
OF THE POWERX TRANSFORMER.
LOCATE AWAY FROM IRRIGATION HEADS.


GFI PROTECTED 120V POWER WITH
WATERPROOF QUTLET COVER

4"X4" REDWOOD POST MOUNTED IN A
CONCRETE FOOTING.


ALL METAL PARTS MUST BE GROUNDED
IN ACCORDANCE TO NEC GUIDELINES.

BOTTOM OF TRANSFORMER CABINET TO
BE A MINIMUM OF 12" ABOVE FINISHED
GRADE.

RUN LOW VOLTAGE CABLES IN 1.50"
GRAY PVC CONDUIT UNTIL THEY ARE
12" BELOW FINISHED GRADE.



SECTION/ELEVATION



PONTENZA X TRANSFORMER POST MOUNT

NOT TO SCALE

FX LUMINAIRE DETAIL